

HD LED Battery Powered Drawer Light SA9030 HD INSTALLATION INSTRUCTIONS

Package Contents

- 1. 1 x HD LED Drawer Light
- 2. 2 x Screws
- 3. 2 x 3M Adhesive pads
- 4. Fixture instructions







Important Safety Information

Please read these instructions carefully before attempting to install this product. It is advisable to keep these instructions in a safe place for further reference. These products must not be modified; if any modifications are made, it may invalidate the warranty and may render the product unsafe. These LED lights operate on 4 x AAA batteries. **This product is for indoor use only. Keep out of moisture and use only in dry rooms.**

Install with included screws or 3M adhesive pads.

Do not use rechargeable batteries. Do not mix new and used batteries. Ensure batteries are inserted with correct polarity.

Effective detection range: <8cm (3 inches)

Safety Instructions

- 1. The light should be mounted onto a secure surface. Position lights where they will not be exposed to steam, splashes, etc.
- 2. When the lamp expires the fixture must be replaced.
- 3. Suitable for cabinet/drawer and decorative lighting.

FEATURES:

This unit has two kinds of sensor switch modes which can be selected by pressing the mode change button.

Mode 1: When the LED sensor is out of the detection range, the light will be off in 15 seconds; if it is within the detection range, the light will be off in 2 seconds.

Mode 2: When the LED sensor is in or out of the detection range, the lamp will turn off automatically in one minute. This mode is not applicable in draws but can be useful in cabinets or other wide open locations. Typical usage includes activation by passing hand through the sensor activation range.

Drivers:

No drivers necessary.

Wattage	0.3W
Voltage	12V
LED Qty	4
Kelvin (Cool White)	5000
LPW	45 lm
Beam Angle	60/240
Lifespan	40000hrs
Width	.67in (17mm)
Depth	0.55in (14mm)
Length	11.93in (303mm)

